

Wireless Charging Cam



Product information

- Help in surveillance out on the go via HD Security discreet camera
- Got a complete functioning Wireless charger
- Active night vision built in with remote access to monitor from a distance

Features

BATTERY	8 hours day time & 3 hours with night vision active
Camera	25fps frame rate
Resolution	1080x720 Video recording mode WITH 100 Degree Angle Coverage
Format	25 Fps frame rate with AVI video format
Voice	built in mic
Storage	supports upto 64GB

Wireless Charging Cam

Notification

push notification via App

What's in the Box

- Charger & cord
- SD card jacket

Compatibility

- MAC or windows are not compatible ,it works with android and apple ios
- Wireless 2.4GHZ 2G network
- App- IOT Thing

SETUP INSTRUCTIONS :

Power and charge :

- Check the power of the product, Device should be fully charged first before installation and testing.
- Active home wifi 2.4Hz Frequency

Setup :

step 1 : make sure you phone is connected to 2G Network

step 2 : plug the device in and wait till the led light turns from blue to red , this takes roughly 30 to 40 seconds

step 3 : get on IOTLIVING App

step 4: click first add and find you device

step 5 : select the room name where you want to install it

step 6 :select YES till you see a scanner enable via phone camera

step 7 : scan the QR Code at the bottom of the device

Wireless Charging Cam

step 8 : the window will require your home internet password , enter the right password , make sure there is no space when you hit next

step 9 : the device will start configuring the app and sync on network

step 10 : once you see successfully configure press the tab which will take you to sync time zone

step 11 : the time zone impacts the recorded video and it fetches the information from your phone time zone

step 12 : save the time zone for device

step 13 : click back and it will pop a message of changing password, you can ignore this message

step 14 : Setup completed

Video available upon request